

RP425 Typical Insertion Loss, 50/50ohm

Mechanicals

15 / 30 AMP

FREQ(MHz)		.15	.5	1	10	30
CM, dB		65	75	75	58	40
DM, dB		65	75	75	75	70

50 AMP

FREQ(MHz)		.15	.5	1	10	30
CM, dB		58	70	70	58	40
DM, dB		60	70	75	70	60

80 AMP

FREQ(MHz)		.15	.5	1	10	30
CM, dB		54	65	65	55	40
DM, dB		55	60	60	50	38

100 AMP

FREQ(MHz)		.15	.5	1	10	30
CM, dB		70	75	75	58	30
DM, dB		55	70	70	60	30

150 AMP



FREQ(MHz)		.15	.5	1	10	30
CM, dB		65	70	70	55	30
DM, dB		50	65	70	60	30

200 AMP

FREQ(MHz)		.15	.5	1	10	30
CM, dB		60	65	60	50	35
DM, dB		55	60	65	60	30

300 AMP

FREQ(MHz)		.15	.5	1	10	30
CM, dB		60	65	60	48	40
DM, dB		55	55	55	50	30



I	A	B	C	D	E	F	MTG
15/30/50	8	3.5	2.75	10	2.5	9	.2x.3
80	10	4	3.25	12	3	11	.25x.5
100/150 200	13	6.6	4.5	15.75	5.12	14.7	.3x.6
300	18	7	5	20	6	19	.3x.6

Dimensions shown for reference only.
Specifications subject to change.

RADIUS POWER
Standard & Custom Products

www.radiuspower.com
PH 714-289-0055
FAX 714-289-214